


# Model - **IPPTR12**

## 12 Channel Surge Protection Panel



### IP PORT PROTECTOR (front panel)

The IPPTR12 is designed to provide 12 channels of multistage surge protection. It is ideally suited for multi-input devices such as a DVR, multiplexer or matrix system.

The IPPTR12 is rack mountable in a standard 19" rack. It installs in minutes and provides a single easy access point for grounding of the unit.

Proper installation is critical to proper operation of the unit. Please read installation instructions completely and insure good ground connections.

# **NITEK**<sup>®</sup>

#### USA Office:

5410 Newport Drive • Rolling Meadows, IL 60008

Phone: (800) 528-4343

Fax: (847) 259-1300

E-mail: [info@nitek.net](mailto:info@nitek.net) • Web: [www.nitek.net](http://www.nitek.net)

#### Europe Office:

De Schans 19-21 2a • 8231 KA Lelysted

Phone: +31(0)320 -230005

Fax: +31(0)320 -282186

E-mail: [info@nitek.nl](mailto:info@nitek.nl) • Web: [www.nitek.nl](http://www.nitek.nl)

# IPPTR12

## 12 Port Video Surge Protection Panel

### INSTALLATION

The IPPTR12 must be properly installed to insure maximum protection. The function of the IPPTR12 is to allow a surge to be routed to ground and to clamp the protected equipment video inputs to a minimum voltage.

There are three key points to remember when installing the IPPTR12. First provide a low impedance connection between the IPPTR12 and your protected equipment. This is best done by keeping the **PROTECTED** network cables as short as possible, ideally 3 feet or less.

Second the system should use a single ground point. Connect the grounding stud of the IPPTR12 to a single ground point. A single ground point is a proper building ground to which equipment grounds are connected. Additionally, AC power line protectors should be used to complete your surge protection strategy.

Finally, the **UNPROTECTED** cables should not be crossed with the **PROTECTED** cables. Crossing cables could provide a path for surge currents to bypass the IPPTR12 protection circuits.

### SPECIFICATION

Size	1RU
Power Requirements	NONE REQUIRED
Connection Method	Standard RJ45 Network Jack (12 In - 12 Out)
Clamping Voltage	60v
Insertion Loss	<0.2dB
Temperature	-10C to +85C
For Use with	10/100 Networks and PoE Distribution systems